

Test Data Sheet

PM-Yb171+_3.1M3


(old: EO-T3080M3-NIR)

S/N:

Resonant electro-optic phase modulator

with

- tunable resonance frequency
- thermal crystal mount



RF properties	Value	Unit
Resonance frequency: f_0 ¹⁾	2753 - 3143	MHz
Preset frequency: f_{set} ¹⁾	3070	MHz
Bandwidth: $\Delta\nu$	6.7	MHz
Quality factor: Q	458	
Required RF power for 1rad @ 935nm ²⁾	35.1	dBm
max. RF power: RF_{max} ³⁾	3	W

Optical properties		
EO crystal	KTP	
Aperture	3x3	mm ²
Wavefront distortion (633nm)	$\lambda/8$	nm
recommended optical intensity (935nm)	<10	W/mm ²
AR coating (R<0.5%)	630 - 1100	nm

¹⁾ at 24°C ²⁾ with 50Ω termination ³⁾ no damage with $RF_{in} < 5W$

Measured modulation

Fig. 1: Oscilloscope trace




Fig. 2: Carrier/sideband ratio




Table 1: Expected modulation

$\beta = 1$ rad	unit	λ_1	λ_2
λ	nm	671	935
P	dBm	31.9	35.1
P	W	1.55	3.26
U	V _p	12.4	18.1
U _{π}	V _p	39.1	56.7
β / U	rad / V	0.08	0.06





Fig.1: Recorded oscilloscope trace retrieved from a test setup as illustrated below.

Fig.2: Squared absolute values of first-kind Bessel functions vs. modulation depth. Vertical lines reveal the ratio between the carrier $|J_0|^2$ and the i^{th} sideband $|J_i|^2$ at a specific β .


Fig.3: Dependency between RF amplitude and modulation depth for different wavelengths. Points on the curve allow to retrieve either the required RF amplitude for a specific/desired β or the max. achievable modulation depth for a given/available RF power.

Table 1: Expected RF-amplitude/-power values and conversion factors for the required wavelength at the reference modulation depth of 1 rad. **Note:** Experimentally recorded modulation depth displayed in Fig.1 might vary from the respective values ($\beta=1$ rad) provided in the table.


Fig. 3: RF-signal amplitude vs. modulation depth



Resonance characteristics




7/6/2018 3:18:21 PM
1328.5170K92-100178-XI



Tuning performance

MAX resonance frequency	$f_0 \text{ max}$	3143	MHz
MIN resonance frequency	$f_0 \text{ min}$	2753	MHz
number of turns	N_{max}	5	
counter clock-wise turns ↻	higher f_0 ↑		
clock-wise turns ↻	lower f_0 ↓		


- use only supplied tuning tool
- actuate tuner carefully
- do not apply too much pressure or torque
- keep tuning tool coaxial
- tuner might not be perfectly orthogonal to box



Handling instructions

- Input laser polarization must be aligned with respect to the white markers on the housing
- Please handle device carefully. Avoid shock. Don't drop.
- After turn on the resonance frequency might drift slightly with applied RF power. Please compensate by tuning the RF drive frequency until steady-state (~min).

Package drawing



Tested by:

Tel: +49 89 2302 9101
 Fax: +49 89 2302 9102
 eMail: mail@qubig.com
 web: www.qubig.com

Qubig GmbH
 Balanstr. 57
 81541 Munich
 Germany